



(11) **EP 0 699 927 A1**

(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
06.03.1996 Bulletin 1996/10

(51) Int Cl.⁶: **G02B 6/34, H04Q 11/00**

(21) Application number: **95305904.5**

(22) Date of filing: **23.08.1995**

(84) Designated Contracting States:
DE FR GB IT




(72) Inventor: **Bernard Glance**
Colts Neck, New Jersey 07722 (US)

(30) Priority: **31.08.1994 US 298820**

(74) Representative:
Watts, Christopher Malcolm Kelway, Dr. et al
AT&T (UK) Ltd.
5, Mornington Road
Woodford Green Essex, IG8 0TU (GB)


(54) **Tunable add/drop optical filtering method and apparatus**

(57) The present invention includes a tunable add/drop filter that utilizes the unique operational characteristics of a wavelength grating router. The filter comprises a $1 \times N$ switch, a wavelength grating router (WGR) having a plurality of inputs and outputs, and a multiplexer. The WGR demultiplexes an incoming wavelength division multiplexed (WDM) signal, providing the frequency components of the WDM signal at different outputs. The WGR outputs include a set of retain outputs that are coupled directly to the multiplexer and a drop output that is connected to a drop line. The particular WDM signal frequency component that is provided to the drop output depends directly on the WGR input at which the WDM signal is received. The $1 \times N$ switch controllably provides the WDM signal to the proper WGR input so that a select frequency is provided at the drop output, which in turn drops the select frequency from the WDM signal. The undropped signals, as well as any added signals are multiplexed into a new WDM signal by the multiplexer.



EP 0 699 927 A1

FIG. 2



Description

Field of the Invention

The present invention relates generally to optical communication systems, and more particularly to add/drop optical filters for use in optical communication systems.

Background of the Invention

Information communication efficiency over an optical fiber transmission system may be increased by optical wavelength division multiplexing. Wavelength division multiplexed (WDM) systems employ WDM signals consisting of a number of different wavelength optical signals, known as carrier signals or channels, to transmit information on optical fiber. Each carrier signal is modulated by one or more information signals. As a result, a significant number of information signals may be transmitted over a single optical fiber using WDM signals.

To facilitate the addition and subtraction of particular carrier signals to or from the WDM signal at different locations on the network, optical add/drop filters are employed. It should be noted that channels within a WDM signal may be distinguished by either their optical wavelength or optical frequency, and the terms frequency and wavelength will be interchangeably referred to for this purpose.

One known type of network employing such filters is the optical ring network. In a ring network, a ring of one or more transmission fibers facilitates communication between several network nodes. In such networks, a node may originate an information signal which is then modulated onto a carrier signal having a certain optical wavelength. The modulated optical signal is subsequently added to the WDM signal for transmission on the ring network to the appropriate destination node or nodes. At the section of the WDM ring located near the destination node, a filter removes or drops the appropriate channel from the WDM signal. The dropped channel or optical signal is then transmitted to the destination node, where the information signal may be demodulated and used.

For further explanation of the details and operations of such networks, see, for example, A.F. Elrefaie, "Multiwavelength Survivable Ring Network Architectures," GLOBECOM '89 Proc., Dallas, Texas (Nov. 1989), and A.F. Elrefaie, et al., "Fiber-Amplifier Cascades with Gain Equalization in Multiwavelength Unidirectional Inter-Office Ring Networks," IEEE Photonics Tech. Letters, Vol. 5, No. 9, pp. 1026-28 (Sept. 1993).

Optical filters capable of dropping and adding signals at specific wavelengths into an optical fiber are essential components in any network utilizing WDM signals including such ring networks.

At present, add/drop filters ordinarily consist of a 1 x N demultiplexer followed by an N x 1 multiplexer. The

first element demultiplexes the frequency components of the input WDM signal, providing the frequency components to its N output ports. A desired frequency component is then dropped by connecting the corresponding output port to a drop line fiber that is further connected to a destination node. The filter's N x 1 multiplexer re-multiplexes the remaining N-1 frequency components or channels, providing the WDM signal to the multiplexer output port. A signal of the same frequency as that of the dropped component may be added to the WDM signal using the unused port of the multiplexer.

One drawback of such filters is that the channel that is added and/or dropped is fixed by the physical configuration of the filter. Once an output port of the N x 1 demultiplexer has been coupled to the drop line fiber, only that coupled channel may be dropped. Such inflexibility is undesirable.

Another prior art filter attempts to overcome this inflexibility by providing an acoustooptic tunable add/drop optical filter. K.-W. Cheung, "Acoustooptic Tunable Filters in Narrowband WDM Networks: System Issues and Network Applications," Journal on Selected Areas in Communications, Vol. 8, No. 6, pp. 1015-25 (Aug. 1990). In this filter, the frequency component that is dropped may be controllably selected without physically reconfiguring the fiber connections.

The acoustooptic filter includes a waveguide substrate having an input port, a grating, an output port and a drop port. The filter also includes a source of acoustic waves which provides an acoustic wave to the grating of the substrate. The acoustic wave causes a particular optical frequency from an input WDM signal to propagate toward the drop port while the remaining optical frequencies propagate towards the output port. The optical frequency which is removed depends upon the frequency of the acoustic wave applied to the grating. Thus, control of the acoustic source allows the filter to be controllably tuned. Wavelength selective space-division optical networks employing this drop/add filter are proposed in the Cheung article, referred to above, at pp. 1022-25. However, it is noteworthy that such acoustooptic tunable filters have the added requirement of a finely-tuned source of acoustic waves.

Summary of the Invention

The present invention includes a tunable add/drop filter that utilizes the unique operational characteristics of a wavelength grating router. The filter comprises a 1 x N switch, a wavelength grating router (WGR) having a plurality of inputs and outputs, and a multiplexer. The WGR demultiplexes an incoming WDM signal, providing the frequency components of the WDM signal at different outputs. The configuration of the frequency components on the WGR outputs depends directly on the WGR input at which the WDM signal is received. One output of the WGR, called the drop output, is connected to a drop line. The 1 x N switch controllably provides the WDM signal

to the proper WGR input so that a select frequency is provided to the drop output, which in turn drops the select frequency from the WDM signal. The undropped signals, as well as any added signals, are multiplexed into a new WDM signal by the multiplexer.

In exemplary embodiments of the present invention, the multiplexer may comprise a star coupler, or a second WGR coupled to a second 1 x N switch.

Other features and embodiments of the present invention will become clear to those of ordinary skill in the art by reference to the drawings and accompanying detailed description.

Brief Description of the Drawings

FIG. 1 illustrates a WDM optical ring network employing tunable add/drop filters operating according to the present invention;

FIG. 2 illustrates an exemplary embodiment of an optical add/drop filter according to the present invention;

FIGS. 2A, 2B and 2C illustrate an overview of the input/output characteristics of the waveguide grating router;

FIG. 3 illustrates an alternative embodiment of an optical add/drop filter according to the present invention;

FIGS. 4, 5 and 6 illustrate the optical spectra of signals appearing at various sampling locations of an experimental prototype of the circuit illustrated in FIG. 2; and

FIG. 7 illustrates a wavelength grating router which may be employed in the filters shown in Figs. 2 and 3.

Detailed Description of the Drawings

FIG. 1 illustrates an exemplary WDM optical ring network 100 which may suitably be a part of a larger communication network, not shown. The network 100 includes a plurality of signal transmitters 110, 112, 114 and 116, a multiplexer 120, two add/drop filters 130 and 140, two network nodes 136 and 146, a demultiplexer 150, a plurality of signal receivers 160, 162, 164 and 166, and optical fibers 125, 138 and 145. The network 100 may suitably include other network nodes similar to the nodes 136 and 146.

The plurality of signal transmitters 110 through 116 are optically coupled to the multiplexer 120. The optical fiber 125 connects the multiplexer 120 to the first remotely located add/drop filter 130. The first add/drop filter 130 is a tunable add/drop filter according to the present invention, and may be, for example, either of the filters dis-

cussed below in connection with FIGs. 2 and 3. The first add/drop filter 130 is connected to the first network node 136 through a drop line 132 and an add line 134. The optical fiber 138 optically couples the first add/drop filter 130 to the second add/drop filter 140, which is also a tunable add/drop filter. The second add/drop filter is connected to the demultiplexer 150 through a length of optical fiber 145. The plurality of signal receivers 160 through 166 are optically coupled to the demultiplexer 150. Each of the receivers 160 through 166 is selectively coupled to one of the transmitters 110 through 116 via an optical switch 170.

In general, the ring network 100 effects communication between the nodes 136 and 146, as well as other nodes, not shown, through the use of information signals modulated onto optical carrier signals or frequency channels. Each node in the network transmits and receives information signals on a single frequency channel of a WDM signal. For example, the first network node 136 communicates on a frequency channel having a frequency F_3 while the second network node 146 communicates on a frequency channel having a frequency F_1 .

In operation, electrical information signals I1, I2, I3 and I4 are provided to the signal sources 110, 112, 114 and 116, respectively. The signal transmitter 110 modulates I1 onto an optical carrier signal having a frequency F_1 , the signal transmitter 112 modulates I2 onto an optical carrier signal having an optical frequency F_2 , the signal transmitter 114 modulates I3 onto an optical carrier signal having an optical frequency F_3 , and the signal transmitter 116 modulates I4 onto an optical carrier signal having an optical frequency F_4 . It is assumed for the purposes of discussion that I3 consists of information signals destined for the first network node 136 while I1 consists of information signals destined for the second network node 146.

The multiplexer 120 receives the four optical carrier signals and multiplexes them into a single WDM optical signal W1 having four modulated frequency components or channels λ_1 , λ_2 , λ_3 and λ_4 . The WDM signal W1 then propagates through the optical fiber 125 to the add/drop filter 130.

When the signal W1 reaches the first add/drop filter 130, a control signal either contained within W1 or provided externally directs the first add/drop filter 130 to remove the frequency component λ_3 from W1. The removed frequency component λ_3 propagates through the drop fiber 132 to the network node 136. At the network node 136 the information signal I3 is demodulated from the optical carrier signal and then stored, used or further transmitted. Another electrical information signal I3' is then modulated onto an optical signal λ_3' having the same frequency as the dropped signal and propagated through the add fiber 134 to the add/drop filter 130. The information signal I3' contains the outgoing information from the network node 136.

The add/drop filter 130 then adds the modulated optical signal λ_3' to the other channels, creating a WDM

optical signal W1' comprising four modulated frequency components λ_1 , λ_2 , λ_3 and λ_4 . The signal W1' propagates through the fiber 138 to the second add/drop filter 140, where another control signal directs the second add/drop filter to remove a different frequency component, for example, λ_1 , from W1', for similar purposes.

In particular, the dropped signal λ_1 is directed to the second network node by the add/drop filter 140 in a similar manner. The network node 146 then stores, uses or further transmits λ_1 . Another electrical information signal I_1' is then modulated onto an optical signal λ_1' having the same frequency as the dropped signal. The add/drop filter 140 multiplexes λ_1' , λ_2 , λ_3 and λ_4 into a WDM signal W1", which then propagates through the fiber 145 to the demultiplexer 150.

The demultiplexer 150 demultiplexes W1" into its frequency components λ_1' , λ_2 , λ_3 and λ_4 and provides them to the signal receivers 160 through 166, respectively. The receivers 160 through 166 demodulate λ_1' , λ_2 , λ_3 and λ_4 respectively and provide I_1' , I_2 , I_3 and I_4 to the switch 170. The switch 170 then directs each information signal to the transmitter corresponding to the frequency channel used by the node to which each information signal is destined. For example, if the network node 136 transmits I_3' to the network node 146, the switch 170 directs I_3' to the first transmitter 110, which modulates I_3' onto the carrier frequency F_1 .

Using the above described method, a central switching office formed by the multiplexer 120, the transmitters 110 through 116, the optical switch 170, the receivers 160 through 166 and the demultiplexer 150 can effect communication between the nodes 136 and 146, and other like nodes on the network 100, using WDM optical signals.

Under certain circumstances, it is desirable to change the frequency channel on which the network node 140 communicates. If, for example, the frequency F_3 becomes particularly lossy due to external factors, then the network node 140 may need to communicate on another available frequency. The filter 130 of the present invention may be controllably switched to provide a different frequency, for example, F_4 , through application of the control signal discussed above. In contrast, prior art filters would ordinarily need to be physically reconfigured to provide a different frequency.

FIG. 2 illustrates a tunable optical add/drop filter 200 according to the present invention that may be implemented in the above system, as well as other WDM networks. The filter 200 exploits the distinctive input/output characteristics of the wavelength grating router, discussed below in connection with FIGS. 2A, 2B and 2C. The filter 200 may be utilized in a WDM optical network to remove at least one controllably selected frequency component from a WDM signal.

The filter 200 includes an input 210, a $1 \times N$ optical switch 215, an $N \times N$ waveguide grating router 225, a star coupler 235, and an output 240, connected in the following manner. The $1 \times N$ optical switch 215 has N

outputs 220₁ through 220_N and an input, which preferably is the filter input 210. The switch 215 may be any suitable optical switch such as a commercially available mechanical optical switch or an optoelectrical switch.

The switch outputs 220₁ through 220_N are coupled to the N inputs of the wavelength grating router (WGR) 225, such that the first switch output 220₁ is connected to the first WGR input 222₁, the second switch output is connected to the second WGR input 222₂, and so forth. The WGR 224 also has N outputs 230₁ through 230_N. Before continuing with a description of the filter 200, it is useful to address the operational characteristics of the WGR 225. The structure of a suitable WGR is discussed in further detail below in connection with FIG. 7, however, FIGS. 2A, 2B and 2C more generally illustrate the WGR input/output characteristics. In FIG. 2A, a WDM signal comprising frequency components λ_1 , λ_2 , ... λ_N is provided at the first input 222₁ of the WGR 225. In this case, the WGR 225 provides λ_1 at its first output 230₁, λ_2 at its second output 230₂ and so forth, providing λ_N at its Nth output 230_N.

In FIG. 2B, the same WDM signal is provided to the second input 222₂ of the WGR 225. The configuration of the frequency components shifts by one output. Thus, in this case, the WGR provides λ_1 at its second output 230₂, λ_2 at its third output 230₃, and so forth, providing λ_{N-1} at its Nth output 230_N. The output shift includes a wraparound, and therefore the frequency component λ_N appears at the first WGR output 230₁. For each subsequent WGR input, the configuration of frequency components on the WGR outputs shifts in a similar manner. Thus, for example, if the WDM signal is provided at the Nth input 222_N, then the WGR 225 provides λ_1 at its Nth output 230_N, λ_2 at its first output 230₁, and λ_3 at its second output 230₂, and so forth, as shown in FIG. 2C.

Returning to the description of the filter 200 shown in FIG. 2, the N outputs of the WGR 225 are divided into a set of N-1 retain outputs, 230₁ through 230_{N-1}, and a drop output 230_N. The set of retain outputs 230₁ through 230_{N-1} are each connected to one of N-1 inputs of the star coupler 235, such that the first WGR output 230₁ is connected to the first star coupler input 234₁, the second WGR output 230₂ is connected to the second star coupler input 234₂, and so forth. The star coupler 135 has a further input 234_N, which is connected to an add line 233. The star coupler 235 may suitably comprise any commercially available star coupler, such as a Gould model 23-40355-14-04801 star coupler. The star coupler 235 also includes an output, which is connected to the filter output 240. The star coupler 235 may be replaced by other suitable multiplexing means, such as a combination of a second WGR and an optical switch, which are discussed below in connection with FIG. 3.

The drop output 230_N of the WGR 225 is connected to a drop line fiber 232. In another embodiment discussed below, more than one drop output may be provided in order to allow more than one channel to be dropped.

The filter 200 as described above operates generally in the following manner. A WDM signal including a plurality of frequency components propagates through a network, not shown, to the filter input 210. Thereafter, the 1 X N optical switch 215 receives the WDM signal, and control signals contained within the received WDM signal or otherwise provided to the switch 215 direct the switch 215 to provide the WDM signal to a particular output, 220_x. The output of the switch 215 at which the WDM signal is provided depends on the channel or frequency component of the signal intended to be dropped.

The signal thereafter propagates from the switch output 220_x to the WGR input 222_x. The WGR 225 then provides at its N outputs 230₁ through 230_N the frequency components of the WDM signal, such that each frequency component appears at a distinct WGR output. Thus, a quantity of N-1 frequency components appear at the set of WGR retain outputs 230₁ through 230_{N-1} and one frequency component appears at the WGR drop output 230_N. As discussed above, the particular WDM frequency component that appears at each WGR output depends directly upon the WGR input at which the WDM signal is received.

The select frequency component that is provided to the WGR drop output 230_N propagates down the drop line fiber 232. That select frequency component may then be provided to a destination such as the network node 136 from FIG. 1, above. The remaining frequency components that are provided to the set of retain outputs of the WGR 225 propagate from the WGR outputs 230₁ through 230_{N-1} to the star coupler inputs 234₁ through 234_{N-1}.

As a result, the control signals determine the frequency to be dropped by instructing the optical switch 215 to provide the WDM signal to the input of the WGR 225 that produces a specific output configuration. Then, in that specific configuration, the select frequency component is provided to the drop output 230_N of the WGR 225. It is to be noted that the use of a presently available mechanical optical switch as the 1 X N switch 215 allows controlled frequency tuning speeds of on the order of .01 seconds. In the alternative, the use of an optoelectronic switch as the switch 215 provides tuning speeds of on the order of nanoseconds.

In addition, an added signal, which comprises an information signal modulated onto a carrier signal having the same frequency as the dropped channel, is provided through an add line 233 to the input 234_N of the star coupler 235. The star coupler 235 then wavelength division multiplexes the remaining signals and the add signal and provides them to the filter output 240. The resulting WDM signal thus includes the original WDM signal with the select frequency component removed, plus the added signal.

FIG. 3 illustrates an alternative embodiment of a tunable optical add/drop filter 300 according to the present invention. The filter 300 comprises an input 310, first and second optical switches 315 and 345, first and second

N x N WGRs 325 and 335, and an output 350. In this embodiment, the combination of the second WGR 335 and the second optical switch 345 replace the star coupler 235 from the filter 200 discussed above in connection with FIG. 2. At present, 1 x N star couplers introduce 1/N attenuation to the optical network, which is more than the WGR and switch combined. As a result, the embodiment illustrated in FIG. 3 provides less attenuation than the embodiment of the filter in FIG. 2.

The first 1 x N optical switch 315 has N outputs 320₁ through 320_N connected to the N inputs 322₁ through 322_N of the first WGR 325 in an analogous manner as in the filter 200 in FIG. 2. The first WGR 325 and the first 1 x N optical switch 315 may suitably be of the type discussed above and illustrated in FIG. 1.

As in FIG. 2, above, the first WGR 325 also comprises N outputs 330₁ through 330_N, including a set of N-1 retain outputs 330₁ through 330_{N-1} and a drop output 330_N. Each of the set of retain outputs 330₁ through 330_{N-1} is connected to one of a set of N-1 inputs of the second WGR 335, such that the first output 330₁ of the WGR 325 is connected to the first input 334₁ of the second WGR 335, the second output 330₂ of the first WGR 325 is connected to the second input 334₂ of the second WGR 335, and so forth. The first WGR drop output 330_N is connected to a drop line fiber 332. The second WGR 335 also includes an add input 334_N that is connected to an add line fiber 333.

The second WGR 335 furthermore includes a set of N outputs 340₁ through 340_N, each of which is connected to one of a set of inputs 342₁ through 342_N of the second 1 x N optical switch 345. The second 1 x N optical switch 345 is of the same structure as the first optical switch 315. The second optical switch 345 is connected to the filter output 350.

The filter 300 operates in a similar manner as the filter 200 in FIG. 2, and may also be utilized in a network to controllably drop and subsequently add a particular frequency component. The primary difference is the technique by which the filter 300 remultiplexes the frequency components of the WDM signal for output.

As before, when a WDM signal is provided at the filter input 310, the first optical switch 315 controllably provides the WDM signal to a select one of its N outputs, 320_x, which then propagates to the WGR 325. The first WGR 325 receives the WDM signal at its Xth input 322_x. The first WGR 325 provides at its outputs 330₁ through 330_N the frequency components of the WDM signal, such that each frequency component appears at a distinct WGR output. The particular configuration of frequency components provided on the WGR outputs depends directly on the WGR input at which the WDM signal is received.

As before, the frequency component that appears at the drop output 330_N of the first WGR is the dropped frequency component. The remaining frequency components are provided to the inputs 334₁ through 334_{N-1} of the second WGR 335. It is to be noted that when a WGR

is used as a multiplexer, the particular output at which the WDM signal is provided depends upon the configuration of frequency components on the WGR inputs. Thus, the second WGR 335 multiplexes the remaining frequency components and provides the multiplexed result to a particular output 340_x which corresponds to the input 322_x of the first WGR 325. To do so, the second WGR 345 is substantially identical in structure or at least has substantially identical input/output characteristics as the first WGR 325.

The second optical switch 345 is also provided with a control signal that directs it to provide the WDM signal, which appears at its input 342_x, to its output which is coupled to the filter output 350. The control of the optical switch 345, whether it be an electrooptic coupler or a mechanical optical switch, is known to those of ordinary skill in the art. If the optical switch 345 is of substantially identical structure as the first optical switch and the two WGRs 325 and 335 have substantially identical characteristics, the same control signal may be provided to the first and second optical switches 305 and 345.

In another alternative embodiment of the filter 200, a plurality of frequency channels may be dropped and/or added. In such an embodiment, the WGR 225 may suitably include a set of M drop outputs and a set of N-M retain outputs. The M outputs would then be connected to M drop fibers and the N-M retain outputs would be connected to the star coupler 235 or other multiplexing means. A set of M add fibers may also be connected to the star coupler 235.

A working example of the filter 200 discussed above in connection with FIG. 2 was constructed wherein the optical switch 215 was a DiCon VX500 low profile 1 X N switch and the star coupler 235 was a Gould 23-40355-14 1 X 4 star coupler. The WGR 225 had a first set of three retain outputs 230₁ through 230₃ connected to three star coupler inputs 234₁ through 234₃, and one drop output 230₄ connected to the drop line fiber 232. The experimental results of the filter are provided in FIGS. 4 through 6. The various components were connected by single mode optical fiber.

FIG. 4 shows the input optical WDM signal, comprising four frequency components 410, 420, 430 and 440, having four distinct evenly-spaced wavelengths. The optical switch 215 was configured to provide the WDM signal to its third output 220₃. The WGR 225 thereafter provided the individual frequency components 410, 420, 430 and 440 to its outputs 230₃, 230₄, 230₁ and 230₂ respectively.

FIG. 5 shows the optical spectrum of the signal appearing on the drop line 232. Because the WDM signal was provided at the third input of the WGR 225, under ideal circumstances only the second frequency component would appear at the drop line 232. In fact, the spectrum shows that the second frequency component 520 was provided to the drop line 233 at a power level of over 25 dB greater than any of the other frequency components. The other frequency components 510, 530 and

540 are present at low power only. Their low power presence is due to cross talk and other limitations of the WGR.

FIG. 6 shows the optical spectrum of the signal appearing at the filter output 240. The dropped frequency component 620 has substantially less optical power than the remaining components 610, 630 and 640. Again, limitations in the WGR 225 are responsible for the presence of the vestige signal 620 in the output. The experimental filter thus effectively dropped the second frequency component, and only the second frequency component from the WDM input signal.

When the optical switch was controlled to provide the WDM signal to a different input of the WGR 225, a different frequency component was dropped from the output optical signal 240. Similar respective power levels were observed at the drop fiber 232 and the output 240.

The present invention thus provides a novel add/drop filter. The use of the WGR and an optical switch allows separate frequency components to be dropped from a single filter without requiring physical reconfiguration of the drop line with respect to the output ports. Furthermore, special acoustooptic devices and acoustic sources are not required as they are in the tunable add/drop filter taught by Cheung, above.

FIG. 7 illustrates an exemplary optical waveguide grating router which may be used in the tunable add/drop filters illustrated in FIGS. 2 and 3. This waveguide grating router is disclosed in U.S. Patent 5,136,671.

It preferably comprises two substantially identical and symmetrically disposed star couplers 10 and 12 connected by waveguides forming a substantially symmetrical optical diffraction grating 14.

FIG. 7 shows an array 16 of N input waveguides radially directed from N input ports toward a focal point F2. Each of the input waveguides has a predetermined width W and is angularly displaced from its adjacent waveguides by an angle α or α .

The star coupler 10 comprises a dielectric slab 18 which forms a free space region having two curved boundaries 18a and 18b. The input waveguides in the array 16 are connected to the free space region 18 in a substantially uniform fashion along boundary 18a. As indicated in FIG. 7, each of those waveguides is separated from adjacent waveguides by a distance t along the boundary 18a.

An array 20 of M output waveguides is radially directed toward a focal point F1. Each of the waveguides in the array 20 has a width W' and is separated from adjacent waveguides in the array 20 by an angular spacing α' . The output waveguides in the array 20 are connected to the free space region 18 in a substantially uniform fashion along boundary 18b. Each of the output waveguides is separated from its neighbors at the boundary 18b by a distance t', as shown in FIG. 7.

The M waveguides of the grating 14 are a symmetric arrangement of waveguides each having length ℓ_g , where s is referenced to the central waveguide in the grating.

Each half of the grating 14 comprises preferably three sections, respectively composed of radial, circular, and equispaced parallel waveguides. Each of the output waveguides in the array 20 is connected to the input of a waveguide in the grating 14. The length of each waveguide in the grating differs from the lengths of all the other waveguides in the grating so that predetermined and different phase shifts are applied to optical signals propagating into the waveguides of the grating from the star coupler 10 because of the different path lengths over which the signals travel in the grating. The outputs of the waveguides in the grating 14 thus have different phases, which are functions of the lengths of the waveguides.

The outputs of the waveguides in the grating 14 are connected to another array 22 of M input waveguide which are radially directed toward a focal point F4. The array 22 connects the output of the grating 14 to the input of the second star coupler 12. Like star coupler 10, star coupler 12 comprises a slab of dielectric material 24 forming a free space region having two curved, preferably circular, boundaries 24_a and 24_b. The array 22 of input waveguides is connected to the free space region in a substantially uniform distribution along boundary 24_a.

An array of N output waveguides are radially directed from N output ports toward a focal point F3. The output waveguides in the array 26 are connected to the free space region 24 in substantially uniform distribution along the boundary 24_b.

In general, when a WDM signal is provided at one of the router inputs in array 16, each of the frequency components of the WDM signal is provided at a distinct output of the output array 26. It is noted that the width of the channels, in other words, the subset of frequencies comprising a frequency component, may be controlled by proper design of the router. The details regarding the operation of the router shown in FIG. 7 are given in U.S. Patent No. 5,136,671.

It is to be understood that the above-described embodiments of the invention are merely illustrative. Other implementations may readily be devised by those skilled in the art which will embody the principles of the invention and fall within the scope thereof.

Claims

1. An optical filter for use with wavelength division multiplexed signals comprising a plurality of frequency components, the optical filter operable to remove at least one frequency component from a wavelength division multiplexed signal, the optical filter comprising:

a) a wavelength grating router, the router including a plurality of inputs and a plurality of outputs, the router operable such that when an input signal comprising a plurality of frequency components

is received at one of the router inputs, each frequency component of the input signal is provided at a distinct output, and the distinct output at which each frequency component is provided is dependant upon the router input at which the input signal is received;

b) an optical switch comprising an input and a plurality of outputs connected to the wavelength grating router, each switch output connected to one of the plurality of router inputs, the switch operable to receive an optical signal at the switch input and provide the received optic signal at a select one of the plurality of switch outputs; and

c) a multiplexer for wavelength division multiplexing a plurality of frequency components, the multiplexer coupled to less than all of the plurality of waveguide grating router outputs.

2. The optical filter of claim 1 wherein the plurality of wavelength grating router outputs comprises a set of one or more drop outputs and a set of one or more retain outputs, each retain output coupled to the multiplexer.
3. The filter of claim 1 or claim 2 further comprising means for controllably selecting one of the plurality of switch outputs at which to provide an optical signal received at the optical switch input.
4. An optical filter for use with wavelength division multiplexed signals comprising a plurality of frequency components, the optical filter operable to remove at least one frequency component from a wavelength division multiplexed signal, the optical filter comprising:

a) a first wavelength grating router, the router including a plurality of inputs and a plurality of outputs, the plurality of outputs further comprising a set of one or more drop outputs and a set of one or more retain outputs, the router operable such that when an input signal including a plurality of frequency components is received at one of the router inputs, each frequency component of the input signal is provided to a distinct router output, and the distinct output at which each frequency component is provided is dependant upon the router input at which the input signal is received;

b) an optical switch comprising an input and a plurality of outputs connected to the first wavelength grating router, each switch output connected to one of the plurality of router inputs, the switch operable to receive an optical signal at

- the switch input and provide the received optical signal at a select one of the plurality of switch outputs;
- c) a second waveguide grating router comprising a first set of inputs and a plurality of outputs, each of the first set of inputs coupled to one of the set of retain outputs of the first wavelength grating router; and
- d) a second optical switch comprising a plurality of inputs and an output, each of the plurality of optical switch inputs connected to one of the plurality of second wavelength grating router outputs, the switch operable to provide at its output an optical signal received at a select one of the plurality of switch inputs.
5. The optical filter of claim 4 wherein the second wavelength grating router comprises a second set of one of more inputs, the second set of inputs connected to one or more signal sources.
6. An optical filter for use with wavelength division multiplexed signals comprising a plurality of frequency components, the optical filter operable to remove at least one frequency component from a wavelength division multiplexed signal, the optical filter comprising:
- a) a wavelength grating router, the router including a plurality of inputs and a plurality of outputs, the plurality of outputs further comprising a set of one or more drop outputs and a set of one or more retain outputs, the router operable such that when an input signal including a plurality of frequency components is received at one of the router inputs, each frequency component of the input signal is provided to a distinct router output, and the distinct output at which each frequency component is provided is dependant upon the router input at which the input signal is received;
- b) an optical switch comprising an input and a plurality of outputs connected to the wavelength grating router, each switch output connected to one of the plurality of router inputs, the switch operable to receive an optical signal at the switch input and provide the received optical signal at a select one of the plurality of switch outputs; and
- c) a star coupler comprising a first set of inputs and an output, each of the first set of inputs coupled to one of the set of retain outputs of the wavelength grating router.
7. The optical filter of claim 6 wherein the star coupler comprises a second set of one of more inputs, the second set of inputs connected to one or more signal sources.
8. The optical filter of any of claims 4 to 7 wherein the wavelength grating router further comprises:
- a first free space region optically coupled to the plurality of inputs;
- a second free space region optically coupled to the plurality of outputs; and
- an optical grating providing optical communication between the first free space region and the second free space region.
9. The filter of any of the preceding claims wherein the optical switch comprises a mechanical optical switch.
10. The filter of any of claims 1 to 8 wherein the optical switch comprises an optoelectrical optical switch.
11. An optical optical filter for use with wavelength division multiplexed signals comprising a plurality of frequency components, the optical filter operable to remove at least one frequency component from a wavelength division multiplexed signal, the optical filter comprising:
- a) a wavelength router comprising
- a plurality of inputs;
- a first free space region optically coupled to the plurality of inputs;
- a second free space region;
- an optical grating providing optical communication between the first free space region and the second free space region;
- a plurality of outputs optically coupled to the second free space region, including at least one drop output and a set of retain outputs;
- b) an optical switch comprising:
- at least one input operable to receive multiplexed optical signals;
- a plurality of outputs operable to provide multiplexed optical signals, the plurality of outputs connected to the plurality of wavelength router inputs;
- c) a means for multiplexing a plurality of frequency components, the multiplexing means coupled to the set of retain outputs of the waveguide router; and
- d) a drop line connected to at least one drop output of the wavelength router.
12. A method of dropping a select frequency from a

wavelength division multiplexed optical (WDM) signal, the WDM signal comprising a plurality of frequency components, the method comprising:

a) controllably providing the WDM signal to a select input of a wavelength grating router (WGR) having a plurality of inputs and a plurality of outputs, the plurality of outputs including a drop output, the WGR operable to demultiplex the WDM signal provided at the select input and further operable to provide the select frequency component to the drop output;

b) propagating the select frequency component from the drop output to a drop line; and

c) multiplexing the plurality of frequency components demultiplexed by the WGR.

13. The method of claim 12 wherein the step a) further comprises:

a) providing a WDM signal to a switch having a plurality of outputs; and

b) controlling said switch to provide the WDM signal to a select output of the plurality of switch outputs.

14. The method of claim 12 or claim 13 wherein step c) further comprises multiplexing a second plurality of frequency components, the second plurality of frequency components comprising the plurality of frequency components substantially without the select frequency component.

15. The method of claim 14 further comprising the step of adding a new frequency component to the second plurality of frequency components.

16. A system for transmitting optical signals in the form of wavelength division multiplexed (WDM) signals, each WDM signal comprising a plurality of frequency components, the system comprising:

a) a central switching office, the central switching office including a multiplexer and a demultiplexer;

b) a tunable optical filter operable to remove at least one frequency component from a WDM signal, the optical filter comprising

a wavelength grating router, the router including a plurality of inputs and a plurality of outputs including at least one drop output, the router operable such that when an input signal comprising a plurality of frequency components is received at one of the router inputs, each fre-

quency component of the input signal is provided at a distinct output, and the distinct output at which each frequency component is provided is dependant upon the router input at which the input signal is received;

an optical switch comprising an input and a plurality of outputs connected to the wavelength grating router, each switch output connected to one of the plurality of router inputs, the switch operable to receive an optical signal at the switch input and provide the received optical signal at a select one of the plurality of switch outputs; and

a multiplexer for wavelength division multiplexing a plurality of frequency components, the multiplexer coupled to less than all of the plurality of waveguide grating router outputs;

c) a length of optical fiber optically coupled to the central switching office multiplexer and the input of the optical switch of the tunable filter;

d) a length of optical fiber optically coupled to the central switching office demultiplexer and the multiplexer of the tunable optical filter; and

e) a network node optically connected to at least one drop output of the wavelength grating router.




FIG. 1






FIG. 2




FIG. 3








FIG. 4**FIG. 5****FIG. 6**

FIG. 7





European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 95 30 5904

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
X	ELECTRONICS LETTERS, vol. 30, no. 16, 4 August 1994 STEVENAGE GB, pages 1327-1328, O.ISHIDA ET AL. 'FDM-channel selection filter employing an arrayed-waveguide grating multiplexer' * the whole document *	1	G02B6/34 H04Q11/00
A	---	4,6, 11-13,16	
A	ELECTRONICS LETTERS, vol. 29, no. 24, 25 November 1993 STEVENAGE GB, pages 2133-2134, Y.TACHIKAWA ET AL. 'Arrayed-waveguide grating add-drop multiplexer with loop-back optical paths' * page 2133 *	1-6,8, 10-12, 14-16	
A	US-A-4 522 462 (LARGE SCOTT F ET AL) 11 June 1985 * column 2, line 1 - line 55; figures 1,2 *	9	TECHNICAL FIELDS SEARCHED (Int.Cl.6)
P,A	---		G02B H04J H04B H04Q
	ELECTRONICS LETTERS, vol. 30, no. 25, 8 December 1994 STEVENAGE GB, pages 2154-2155, O.ISHIDA 'FDM-channel selection filter using arrayed-waveguide grating multiplexer with input and output switches' * page 2154, left column - page 2155, right column; figure 1 * ---	1,4,6, 11,12,16	
The present search report has been drawn up for all claims			
Place of search BERLIN		Date of completion of the search 23 November 1995	Examiner von Moers, F
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure F : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons</p> <p>& : member of the same patent family, corresponding document</p>			

EPO FORM 1501 (12/92) (P04C01)



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 95 30 5904

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
P, A	<p>ELECTRONICS LETTERS, vol. 30, no. 18, 1 September 1994 STEVENAGE GB, pages 1504-1506, Y.TACHIKAWA ET AL. 'Lightwave transrouter based on arrayed-waveguide grating multiplexer' * page 1505; figure 1 *</p> <p>-----</p>	1, 4, 6, 11, 12, 16	
			TECHNICAL FIELDS SEARCHED (Int.Cl.6)
The present search report has been drawn up for all claims			
Place of search BERLIN		Date of completion of the search 23 November 1995	Examiner von Moers, F
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

EPO FORM 1503 03.81 (P04C01)